WC8 SERIES

Split-Core Current Transformers

WC8 is the largest split-core series designed for heavy commercial and industrial applications. Completely encased in thermoplastic housing, this CT is the preferred choice for high Current monitoring. The swing mechanism allows electricians to install at ease and glove friendly. This CT has the WC's trademark ergonomic secured Arc-Latch™ feature along with locking and servicing date tag provision. Install with confidence from made in America design, quality and assembly!

MECHANICAL

Window Size 4.38" x 7.72" [111.13mm x 196.19mm] Wire Leads 6ft [1.8m] 16AWG black/white twisted

UL1015 105°C 600V

Operating Temperature -15°C to 80°C (90% Rel. Hum.)

6,600ft [2012m] Altitude Weight 10.0Lbs [4.54Kg]

Metal knob for locking or date tag **Keying Hole** Arc-Latch™ for EZ-Open, no tool Ergonomic

ELECTRICAL

Primary Input (max.) 5000A, AC Sine-wave 50/60Hz

Secondary Output 5A, full-scale

Accuracy (typical) 0.5%

Linearity 10% - 120%

White (X1—Hi), Black (X2—Low) Polarity

Phase Direction Arrow points toward Load

40-400Hz Frequency

REGULATORY STANDARDS

Voltage Rating 600V AC, BIL 10KV AC Full-wave

UL94V-0 flame retardant plastic, CATIII Construction

Double insulations (optional)

Standards UL2808, ANSI C57.13 & IEC61010-1

CSA C22.2 61010-1-12 & CE Mark

INSTALLATION

For indoor use only. Turn off power source before working on CTs. Observe X1X2 polarity and read manufacture's instructions of the equipment you are connecting to CTs for proper installation guide. Professional installations required for safe handling and operation.



WATTCORE INC | Core Solutions for Energy Management™ 6208 Oakton Street

Morton Grove, IL 60053 (USA)

571.482.6777 | sales@wattcore.com | www.wattcore.com














MODELS


MODEL	RATIO*	ACCURACY	BURDEN (VA)
WC8-2000-RA5	2000:5A	0.5	12.0
WC8-3000-RA5	3000:5A	0.5	18.3
WC8-4000-RA5	4000:5A	0.5	22.0
WC8-5000-RA5	5000:5A	0.5	31.3

^{*}Custom ratio outputs available in mV, V & mA

DIMENSIONS [mm]



SCHEMATIC





De-energize source before installation! Observe local and national electrical codes for safety and compliance. Licensed electricians required. Use precaution when working with electricity!